

# VBAR-803

LED Bars

## DMX mode 1: d.P1

Channel	Value	Description
CH1	0-255	Red
CH2	0-255	Green
CH3	0-255	Blue
CH4	0-255	Master dimmer
CH5	0-255	Flash

## DMX mode 2: d.P2

Channel	Value	Description
CH 1	0	OFF
	1-50	Seven_ color _dream
	51-101	Seven_ color _change
	102-152	Red_ color _dream
	153-203	Green_ color _dream
	204-255	Blue_ color _dream
CH 2	0-255	Speed
CH 3	0-255	Flash