

# VLED 603

LED Par

## DMX mode 1: 1CH

No	Value	Function
1	0	No use
2	1-22	red
3	23-45	green
4	46-68	blue
5	69-91	blue-green
6	92-114	yellow
7	115-137	orange
8	138-160	pink
9	161-183	purple
10	184-206	Dark blue
11	207-229	Pale green
12	230-252	white
13	253-255	Warm white

## DMX mode 2: 3CH

Channel	Value	Function
CH1	0-255	RED
CH2	0-255	GREEN
CH3	0-255	BLUE

## DMX mode 3: 4CH

Channel	Value	Function
CH1	0-255	MASTER DIMMER
CH2	0-255	RED
CH3	0-255	GREEN
CH4	0-255	BLUE

## DMX mode 4: 6CH

Channel	Value		Function
CH1	0-255	Main adjustment	MASTER DIMMER
CH 2	Red adjustment	0-255	Red adjustment 0-255
	Choose the static color it is available when the sixth channel is 0-25	0-8	R (255)
		9-17	R (255) G (50)
		18-26	R (255) G (150)
		27-35	R (255) G (255)
		36-44	R (200) G (255)
		45-53	R (100) G (255)
		54-62	R (40) G (255)
		63-71	G (255)
		72-80	G (255) B (50)
		81-89	G (255) B (150)
		90-98	G (255) B (255)
		99-107	G (150) B (255)
		108-116	G (50) B (255)
		117-125	B (255)
		126-134	R (50) B (255)
		135-143	R (150) B (250)
		144-152	R (255) B (255)
		153-161	R (220) B (50)
		162-170	R (150) G (50) B (100)
		171-179	R (50) G (180) B (220)
		180-188	R (50) G (220) B (100)
		189-197	R (150) G (220)
		198-206	R (150) B (220)



## DMX mode 4: 6CH

Channel	Value		Function
CH 2	Choose the static color it is available when the sixth channel is 0-25	207-215	G (180) B (220)
		216-224	G (220) B (50)
		225-233	R (220) G (100) B (50)
		234-242	R (220) G (200) B (100)
		243-251	R (255) G (200) B (150)
		252-255	R (255) G (255) B (255)
	Speed adjustment (control the CH6(26-255)speed)	0-255	0-255 slow-fast
CH 3	0-255		Green adjustment 0-255
CH 4	0-255		Blue adjustment 0-255
CH 5	0-9		NO FUNCTION
	10-255		Strobe (slow-fast )
CH 6	0-25		You can choose the 29 kinds of static color through the second channel
	26-51		Pr02 the seven color s gradual change
	52-77		Pr03 three color s gradual change
	78-103		Pr04 seven color s saltus step
	104-129		Pr05 three color s saltus step
	130-155		Pr06 dream 1
	156-181		Pr07 dream 2
	182-207		Pr08 red gradual change
	208-233		Pr09 green gradual change
	234-255		Pr10 blue gradual change

