

# VPL EXTREME

Moving head

	Value	Function
	115-119	No function
	120-124	Reset
	125-129	No function
9 LEDMICRO	0-3	No MACRO function
	4-67	Fixed MACRO function, RGB LED interchange
	68-131	Fixed MACRO function, RGBW LED interchange
	132-255	LED MICRO function
10 RED	0-255	Dark - Bright dimmer, Color macro Adjust red LED dimmer
11 GREEN	0-255	Dark - Bright dimmer, Color macro Adjust green LED dimmer
12 BLUE	0-255	Dark - Bright dimmer, Color macro Adjust blue LED dimmer
13 WHITE	0-255	Dark - Bright dimmer, Color macro Adjust white LED dimmer
14 BEAM CTC	0-1 2-255	No function BEAM CTC
15 STROBE 2	0-255	Light off for 0-5.10 seconds
16 STROBE 3	0-255	Light up in 0-5.10 seconds
17 STROBE 4	0-255	Bright keep in 0-5.10 seconds
18 STROBE 5	0-255	Light off in 0-5.10 seconds
19 FADE	0-255	Aura speed (fast-slow)
20 HA.STROBE	0-1 2-64 65-127 128-190 191-253 254-255	Shutter open Closing pulse (slow-fast) Opening pulse (slow-fast) Adjust random shutter (slow-fast) Adjust random shutter Shutter open
21HA.DIMMER	0-255	Dark to bright aura dimmer
22HA.LEDMicro	0-3 4-67 69-131 132-255	No Macro function Fixed Macro function, RGB aura interchange Fixed macro function, RGBW Aura interchange, Aura macro function

	Value	Function
23HA.RED	0-255	Dark - Bright dimmer, Color macro Adjust red LED aura
24HA.GREEN	0-255	Dark - Bright dimmer, Color macro Adjust green LED aura
25HA.BLUE	0-255	Dark - Bright dimmer, Color macro Adjust blue LED aura

